

**Table 2. Special Lynx Earthing Nut Specifications for use on single cables with protective conductors sized to BS7671 Table 54G**

Lynx stock Code	Thread size mm	Connection hole size	Conductor size sq mm	Protective Conductor sq mm	Kompress Terminal	Takbro Terminal	Davico-Krimpit Terminal	SWA Terminal TQ Range	Hexagon size mm	Nut thickness mm	Number of teeth	Connecting screw style.
PEN 25S	25	M10	50	25	CT25-10	TU25-10	D25-10	HD25-10	45	20	6	BZP Stud+Nut
PEN 25S	25	M10	70	35	CT35-10	TU35-10	D35-10	HD35-10	45	20	6	BZP Stud+Nut
PEN 25S	25	M10	95	50	CT50-10	TU50-10	D50-10	HD50-10	45	20	6	BZP Stud+Nut
PEN 32S	32	M10	120	70	CT70-10	TU95-10	D70-10	HD70-10	51	25	6	BZP Stud+Nut
PEN 32S	32	M10	150	95	CT95-10	TU95-10	D95-10*	HD95-10	51	25	6	BZP Stud+Nut
PEN 32S	32	M10	185	95	CT95-10	TU95-10	D95-10*	HD95-10	51	25	6	BZP Stud+Nut
PEN 40S	40	M12	240	120	CT120-12	TU120-12*	D120-12	HD120-12	66	31	6	BZP Stud+Nut
PEN 40S	40	M12	300	150	CT150-12	TU150-12*	D150-12*	HD150-12*	66	31	6	BZP Stud+Nut
PEN 50S	50	M16	400	240	CT240-16	TU240-16	D240-16	HD240-16	80	44	6	BZP Stud+Nut
PEN 50S	50	M16	500	300	CT300-16	TU300-16	D300-16	HD300-16	80	44	6	BZP Stud+Nut
Special order only. Conductor size for guidance only. Nut should be sized to fit gland which is the closest fit to the size of cable being used.					*Cannot be fitted parallel with conductors.							With BZP Washer